

The FS100 Series (medium amp) may be used to control inductive, incandescent, or resistive loads. Input voltages of 24, 120, or 230VAC are available. Factory fixed flash rate of 90 FPM or may be ordered with a fixed, custom flash rate ranging from 10 to 300 FPM. Encapsulation provides protection against shock, vibration, and humidity. This group of solid-state flashers has proven reliability with years of use throughout the world.

Operation

Upon application of input voltage, the T2 OFF time begins. At the end of the OFF time, the T1 ON time begins and the load energizes. At the end of T1, T2 begins and the load de-energizes. This cycle repeats until input voltage is removed.

Reset: Removing input voltage resets the output and the sequence to T2.

For more information see:

- Appendix A, page 164 for Flasher (OFF First) function.
- Appendix B, page, 165, Figure 1 for dimensional drawing.
- Appendix C, page 168, Figure 3 for connection diagram.


Order Table:

Input Voltage	Rating	Part Number
24VAC	3A	FS143
120VAC	3A	FS152
230VAC	3A	FS162

Add the suffix "-##" to any part number to indicate the custom flash rate.

Specifications

Technical Data		Maximum Load Rating 3A steady state
Operation	OFF/ON solid-state flasher (continuous duty)	Inrush 10 times steady state current
Flash Rate	Fixed at 90 FPM ±10%	Mechanical
Custom Flash Rates	10 - 300 FPM ±10%	Mounting Surface mount with one #10 (M5 x 0.8) screw
ON/OFF Ratio	≅ 50%	Dimensions 2 x 2 x 1.21 in. (50.8 x 50.8 x 30.7 mm)
Input		Termination 0.25 in. (6.35 mm) male quick connect terminals
Voltage/Frequency	24, 120, or 230VAC ±15%/50/60 Hz	Protection
Output		Circuitry Encapsulated
Load Type	Inductive, resistive, or incandescent	Environmental
Output	Fullwave AC, solid state, SPST	Operating / Storage Temperature -20° to 60°C / -40° to 85°C
		Weight ≅ 2.2 oz (62 g)



The FS200 Series may be used to control inductive, incandescent, or resistive loads. Input voltages of 12, 24, 36, 48, or 110VDC are available. Factory fixed flash rate of 90 FPM or may be ordered with a fixed custom flash rate ranging from 10 to 180 FPM. Encapsulation provides protection against shock, vibration, and humidity. Uniform performance, high inrush current capability, and low RFI, make this series ideal for general industrial applications.

Operation

Upon application of input voltage, the T2 OFF time begins. At the end of the OFF time, the T1 ON time begins and the load energizes. At the end of T1, T2 begins and the load de-energizes. This cycle repeats until input voltage is removed.

Reset: Removing input voltage resets the output and the sequence to T2.

For more information see:

- Appendix A, page 164 for Flasher (OFF First) function.
- Appendix B, page, 165, Figure 1 for dimensional drawing.
- Appendix C, page 168, Figure 4 for connection diagram.

Order Table:




Input Voltage	Rating	Part Number
12VDC ±20%	3A	FS219
24VDC ±20%	3A	FS224
36VDC ±20%	1A	FS236
48VDC ±15%	0.75A	FS248
110VDC ±15%	0.25A	FS290

Specifications

Technical Data		Inrush 10 times steady state current
Operation	OFF/ON solid-state flasher (continuous duty)	Mechanical
Flash Rate	Fixed at 90 FPM ±10%	Mounting Surface mount with one #10 (M5 x 0.8) screw
Custom Flash Rate	10 - 180 FPM	Dimensions 2 x 2 x 1.21 in. (50.8 x 50.8 x 30.7 mm)
ON/OFF Ratio	≅ 50%	Termination 0.25 in. (6.35 mm) male quick connect terminals
Input		Protection
Voltage	12, 24, 36, 48, or 110VDC	Circuitry Encapsulated
Output		Environmental
Load Type	Inductive, resistive, or incandescent	Operating / Storage Temperature -20° to 60°C / -40° to 85°C
Maximum Load Rating	0.25 - 3A steady state	Weight ≅ 2.2 oz (62 g)
OFF State Leakage Current		
12 & 24VDC	≅ 250 µA	

Features:

- Fixed at 90 FPM
- Custom flash rate 10 - 300 FPM
- Switches inrush currents up to 30A
- 24, 120, or 230VAC input voltages
- Totally solid state & encapsulated

Approvals:   

Auxiliary Products:

- **Female quick connect:**
P/N: P1015-64 (AWG 14/16)
- **Quick connect to screw adaptor:**
P/N: P1015-18
- **Mounting bracket:** P/N: P1023-6
- **DIN rail:** P/N: C103PM (Al)
- **DIN rail adaptor:** P/N: P1023-20

Available Models:

FS143	FS152-60
FS152	FS162
FS152-30	FS162-30
FS152-50	

If desired part number is not listed, please call us to see if it is technically possible to build.

Features:

- Fixed at 90 FPM
- Custom flash rate 10 - 180 FPM
- 3A, SPST output contact
- 12 to 110VDC input voltages in 5 ranges
- Totally solid state & encapsulated
- 0.25 in. (6.35 mm) male quick connects

Auxiliary Products:

- **Female quick connect:**
P/N: P1015-64 (AWG 14/16)
- **Quick connect to screw adaptor:**
P/N: P1015-18
- **Mounting bracket:** P/N: P1023-6
- **DIN rail:** P/N: C103PM (Al)
- **DIN rail adaptor:** P/N: P1023-20

Available Models:

FS224

If desired part number is not listed, please call us to see if it is technically possible to build.